

Identifying the pins of a GLCD 12864

Vdd 5V	Vdd 5V	Vdd 5V	Vdd 5V	1	Vss 0V	Vss 0V	Vss 0V
Vss 0V	Vss 0V	Vss 0V	Vss 0V	2	Vdd 5V	Vdd 5V	Vdd 5V
Vo	Vo	Vo	Vo	3	Vo	Vo	Vo
DB0	DB0	DB0	DB0	4	D -I	D -I	D -I
DB1	DB1	DB1	DB1	5	R -W	R -W	R -W
DB2	DB2	DB2	DB2	6	E	E	E
DB3	DB3	DB3	DB3	7	DB0	DB0	DB0
DB4	DB4	DB4	DB4	8	DB1	DB1	DB1
DB5	DB5	DB5	DB5	9	DB2	DB2	DB2
DB6	DB6	DB6	DB6	10	DB3	DB3	DB3
DB7	DB7	DB7	DB7	11	DB4	DB4	DB4
CS1	-CS1	-CS1	-CS1	12	DB5	DB5	DB5
CS2	-CS2	-CS2	-CS2	13	DB6	DB6	DB6
-RST	-RST	-RST	-RST	14	DB7	DB7	DB7
R -W	R -W	R -W	R -W	15	CS1	CS1	CS1
D -I	D -I	D -I	D -I	16	CS2	CS2	CS2
E	E	E	E	17	-RST	-RST	RST
Vee	Vee	Vee	Vee	18	Vee	Vee	Vee
A	A	A	A	19	K	K	A
K	K	K	K	20	A	A	K